

RC6502 Memory Map

8K SECTION			1K SECTION		DETAILS			Comparison		BLOCK SIZE		
START	END		START	END		START	END	APPLE-1	RC6502			
8K7	\$E000	\$FFF		\$FC00	\$FFFF	WozMon	\$FF00	\$FFFF	ROM	28C64 EEPROM	256	
				\$F800	\$F9FF	Krusader Assembler	\$F000	\$FCFF	(free)			768
				\$F400	\$F7FF							1 024
				\$F000	\$F3FF							1 024
				\$EC00	\$EFFF	Integer Basic	\$E000	\$EFFF				1 024
				\$E800	\$EBFF							1 024
				\$E400	\$E7FF							1 024
				\$E000	\$E3FF							1 024
8K6	\$C000	\$DFFF		\$DC00	\$DFFF	Terminal section			(mirror)	(mirror)	4 096	
				\$D800	\$D9FF							
				\$D400	\$D7FF							
				\$D000	\$D3FF		\$D010	\$D013	MC6821	MC6821		
				\$CC00	\$CFFF			(free)		1 024		
				\$C800	\$CBFF					1 024		
				\$C400	\$C7FF					1 024		
	\$C000	\$C3FF					1 024					
8K5	\$A000	\$BFFF								8 192		
8K4	\$8000	\$9FFF								8 192		
8K3	\$6000	\$7FFF								8 192		
8K2	\$4000	\$5FFF								8 192		
8K1	\$2000	\$3FFF								8 192		
8K0	\$0000	\$1FF	K7	\$1C00	\$1FFF				4K RAM	62256 Static RAM	1 024	
			K6	\$1800	\$1BFF						1 024	
			K5	\$1400	\$17FF						1 024	
			K4	\$1000	\$13FF						1 024	
			K3	\$0C00	\$0FFF						1 024	
			K2	\$0800	\$0BFF						1 024	
			K1	\$0400	\$07FF						1 024	
				(free)	\$0200	\$03FF						
				(stack)	\$0100	\$01FF					1 024	
	(page 0)	\$0000	\$00FF									
										65 536		