



**Description:**  
This package contains six inverters.

**Mode of operation:**  
All six inverters can be used independently of one another.  
For each inverter, a low input gives a high output and vice versa.  
The 7414 contains six inverters with Schmitt-trigger inputs and has the same pinout.

**Application:**  
Logical inversion, pulse shaping, oscillators

<b>Data:</b> Propagation delay	ns	10	6	2.75	3.5	6	33	9.5	3
	Supply current	mA	12	2	8	6.9	26	1.2	3
<b>Families:</b>		Std	ALS	AS	F	H	L	LS	S
		●	●	●	●	●	●	●	●

**Hex INVERTER**

**7404**